



"Telecommunication Products to solve Telecommunication Problems"

HT-878-POH

Promotion-On-Hold Instructions

Introduction

The HT-878-POH is a two line business telephone that has a built in Promotion-On-Hold adapter. This adapter provides Promotion-On-Hold **ONLY** when calls are placed ON HOLD from this specific phone. When other telephones, that share the same lines, are placed ON HOLD, promotion will not be played. If you wish to have Promotion-On-Hold from several phones, multiple HT-878-POH phones can be used. In this case an audio source must be connected to each of the HT-878-POH telephones.

Audio Source

The HT-878-POH has an AUDIO IN jack on the back of the phone. It is a PHONO jack, also referred to as an RCA jack. An external audio source with either a headphone jack or an 8 ohm output (speaker) must can be attached. Commonly used audio sources are: CD players (use small boom box type), digital players, or computers. The main requirements of the audio source is that it has:

- 1- An adjustable volume, audio output. Either headphone or speaker out.
- 2- The ability to REPEAT play 24 hours a day, 7 days a week.
- 3- 115VAC powered (not battery powered)

If you use a CD player DO NOT use a portable type. These units generally do not have enough output audio power. We suggest a small boom box type. Make sure that it has a power cord, a headphone jack, and has a REPEAT mode.

Speakerphone Operation

The speakerphone portion of this phone has low volume and is not very practical to use. For this reason we do not suggest that you use this phone in the speakerphone mode.

Installation

- 1- Connect the audio source to the phone. The supplied audio cable is used with CD players. If another type of source is used, you might have to purchase another audio cable.
- 2- Connect the telephone to the telephone jack with the supplied telephone cord. If both line 1 and 2 are on the same telephone jack, make sure that you use the Dark Gray modular cord.